

### Installation Notes :

**Locking Note**  
Always fit the Tranzil (lock suppressor) supplied.

**Cable requirements :**  
It is recommended that cables are star wired to the video monitors from the entrance panel

Maximum recommended overall distance for CW1308 BT spec. twisted paired cable run is

0 - 100 metres	VCM/60	(see diagram)
100 - 200 metres	15 & 0	- 2.5mm dia.
	1 & 2	- RG59 coaxial cable
	3, 4, 9	- 0.5mm dia

For short cable runs up to 25 metres (although not ideal) you may use CW1308 or CAT5 cable. Treat R1 + R2 as a pair, R3 + R4 as a pair, 0 + 9 as a pair and a pair for wire 15.

Make connections as per diagram in order to avoid interference.

