

## REF. 3233 DUOX PLUS BASIC RELAY



Dimensions(width,height, depth ):106x86x31mm

DIN 6 rail mounting (including side fixing brackets to screw, width 106 mm). Eliminating the lateral fixing brackets for the screws the

This relay allows the most basic and common functions to be carried out.

Using jumper JP1, the relay can be programmed as:

Block Relay (Default value: block = 00): Only the devices in that BLOCK can activate the relay (outdoor panels, guard unit or monitors / telephones)

General Entrance Relay: All users of the installation can activate the relay.

The relay can be programmed to activate with the following actions :

Door opening.

F1 (default activation parameter).

F2

Call from the panel or concierge.

The relay activation time can also be programmed: [1 s, 99 s]. The factory default is 4 s.

### CONNECTIONS

Bus Input: to connect the DUOX PLUS bus.

### ACCESORIES

---

## FEATURES

---

Dimensions(width,height, depth) :106x86x31 mm DIN 6 rail mounting (including side fixing brackets to screw, width 106 mm). Eliminating the lateral fixing brackets for the screws the width is 89 mm (DIN 5).

Standby consumption: 1.2 W

Maximum consumption: 7.2 W

Operating System: [-5°C,40°C]

Humidity: [5%,95%]

Power Supply: 18-24VCC