

 Drawing Reference
 1 D
 n H
 1 E / 250
 10.10.08

 Audio Diagram
 Handsets
 Entrances
 with DC250
 Date

Two entrance audio door entry system - calling n telephone(s)

Installation Notes:

Cable Requirements

Make connections as per diagram in order to avoid interference. CW1308 telephone cable is suitable for distances up to 200 metres. For longer cable runs you should increase the dimensions of the cores according to the chart.

Trm	Wire Function	200	metres 300
1 2 6 9 C7	Loudspeaker Microphone Common -ve Lock release Call tone	0.5 0.5 0.8 0.5 0.5	0.8 0.8 1.0 0.8 0.8
	Diameter of conductors mm		

Please Note

Please make connections as shown in the diagram. TWO wires for terminal 6 of the telephone. White / Green & White / Blue are shown. This is intentional and should be followed for best results.

Locking Note

The lock time is set by the keypad. Always fit the Tranzil (lock suppressor) supplied. You may connect fail open or fail locked locking without the need for aditional relays.

Telephone

You may call up to 3 telephones simultaneously. Alternative telephones are AN9102S, AN7577S.

Spare button

One push button is available for other functions (eg. opening a second lock) marked Au/Au. This is a push to make momentary switch.

DC250

The DC250 card reader controller instructions should be read in cunjunction with this diagram. The lock operating time is set by the timer in the DC250.

Trade Button

Connect 'TRADE' button the same as 'Egress Button'. Add 5200 time clock in series if required.





