



Notes :

When current is drawn from PS (entrance 1 or 2) the relay will latch to the calling entrance for approx. 20 seconds or the duration of the call (whichever is longer). The other entrance, if called, will give an engaged tone.

Site the power supply (9007) close to the relay (9432).

Make connections as per diagram in order to avoid interference.

Locking Device Options

For ALL 12v dc locks move link ## between 'lock' & DC.

For FAIL LOCKED use NO
For FAIL UNLOCKED use NC

12v dc FAIL UNLOCKED	12v dc FAIL LOCKED
PSU DC — []	PSU DC — []
9432 NC — []	9432 NO — []