

2E AK 1 D 13.07.04 Drawing Reference AK5343 relay Audio Diagram Handsets **Entrances** Date

Two entrance audio door entry system - calling n telephone(s). System uses AK5343 relay

Installation Notes:

Cable Requirements

Common -ve

Lock release

Call tone

Make connections as per diagram in order to avoid interference. CW1308 telephone cable is suitable for distances up to 200 metres.

For longer cable runs you should increase the dimensions of the cores according to the chart.

Wire metres 300 Trm **Function** 200 0.5 0.5 0.8 Loudspeaker Microphone 0.8 1.0

Diameter of conductors mm

0.5

0.5

8.0

0.8

Please Note

Please make connections as shown in the diagram. TWO wires for terminal 6 of the telephone. White / Green & White / Blue are shown. This is intentional and should be followed for best results.

Locking Note

The lock time is set by the 9307/2. Always fit the Tranzil (lock suppressor) supplied. You may connect fail open or fail locked locking without the need for aditional relays.

Telephone


You may call up to 3 telephones simultaneously. Alternative telephones are AN0002, AN7320, AN7577.

Spare button

One push button is available for other functions (eg. opening a second lock) marked Au/Au. This is a push to make momentary switche.

Trade button

Connect 'TRADE' button the same as 'Egress Button'. Add 5200 time clock in series if required.




N/O

N/C

12V DC FAIL LOCKED


illustrated with transil fitted



9307/2 lock timer relay (1-40s)

12V DC FAIL LOCKED

illustrated with transil fitted



9307/1

power supply

Mains

9307/2 lock timer relay (1-40s)